

aquatics

Ω
OMEGA
ELECTRONICS

Water-polo options

If you want the best, buy an Omega Electronics product.



Shot Clocks

Electromagnetic two digit display for the countdown of the 35 seconds.

As soon as 0 time is reached an acoustic signal is emitted from the integrated powerful horn (104dB). The shot clocks runs on a battery; this is essential for any device that must be located beside a swimming pool. Connected and synchronised with the main timing device ARES, they follow the START/STOP commands of the referee. The slanted construction with a wider base makes the display stable. The designed 23 cm height of the digits assures an excellent visibility for the players as well as for the seated public. The Plexiglas on the front side protects the displays from water damage.



Horn AGH1

This powerful acoustic horn is used to signal the end of a game or the time-outs in a very effective way. The horn works with an external or battery 115/230V. It can be located next to the swimming pool and is simple to fix permanently on a wall. The horn is connected to the main ARES timing device.

TECHNICAL CHARACTERISTICS **SHOT CLOCKS**

| | |
|---------------------|---------------------------------|
| Part number | 3303-700 |
| Battery autonomy | 12 hours |
| Charger | Lead accumulator 12V/7Ah |
| Dimensions | 430 x 530 x 130 x 250 mm |
| Height of digits | 230 mm |
| Protection IP | IP54 |
| Horn sound | 104 dB |
| Working temperature | 0° to + 40°C |
| Weight | 8.200 kg |
| Consumption | stand-by: 35mA, working: 540 mA |

TECHNICAL CHARACTERISTICS **HORN AGH1**

| | |
|----------------------|-----------------------------------|
| Part number | 3084-900 |
| Humidity | 80% without condensation |
| External battery | 12V DC |
| Charger | 115/230V 50/60Hz 1,6/0,8A |
| Dimensions | 210 x 350 x 225 mm |
| Consumption | 12A/12V with sound, 20mA stand-by |
| Horn with compressor | 117 dB |
| Working temperature | 0° to + 40°C |
| Weight | 7.800 kg |

OPTIONS



- **2872-003 Handtop OIT3**
With 3m coiled cable and banana plug.



- **3288-600 Start-Stop Switch**
Used for Start-Stop game time and for Shot Clocks. To be connected on ARES.



- **3285-618 Set MTL Water Polo - Hand terminals**
2 MTL (OMT) connected to ARES to administer team players. Operation next to the swimming pool border. The assigned players in water can be shown on an alphanumeric scoreboard.

Represented by:

The information contained within this document may be modified without warning. Omega Electronics cannot be held responsible for errors within this document nor for any subsequent nor consequential damages (including loss of profit) arising from its provision, nor performance or use of products described herein, which will be covered by another guarantee, contract or other legal document.

OMEGA ELECTRONICS SA • P.O. BOX 4161 • RUE DES PRÉS 149 • CH-2500 BIENNE 4, SWITZERLAND
PHONE ++41 32 3433 711 • FAX ++41 32 3433 808 • e-mail: info@omega-electronics.ch • Web: http://www.omega-electronics.ch



A COMPANY OF THE **SWATCH GROUP**